



Sardinian Style

Sardinian Style is an easy way to build simple trx, or tx or rx, solid state or glowbugs.

Our scouts and homebrewers are really proud when they build their own radio on a simple wooden table, then turn it on and call CQ first time.....you know what I mean ☺....

Sardinian Style building means (see photos) :



Figure 1



Figure 2



Figure 3

1.-stick a copy of the schematic diagram, having suitable size, on a table (a Pixie II can be hosted on a 12x15x2,5 cm surface).

2.-choose the connection points where you'll fix the 60-70% of each 20x1,2 mm brass nail (no steel) into the the wood.(At least 35 nails for a Pixie).

3.-solder to nails the signal, vdc and ground lines, following the schematic diagram, with tin copper wire.

4.-solder to nails the required components (each component will be assembled over his schematic symbol).

5.-Connect the key, antenna, battery then.....we say :

"Check and Adjust for Minimum Smoke" (CAMS ☺)

...And call CQ CQ ..☺..

Sardinia QRP Club